3. Electrical Parts List

Location no	Code no.	Description; Specifiation	Remarks
		****** MCD-HF920 Parts List ******	
	4302-001087	BATTERY-NIH(2ND);1.2V,1350MAH,RECTANGULA	
	AH44-00023J	ADAPTOR;-,-,120V,60HZ,4.5VDC+/-0.3V,0.	
CD DECK	AH59-01105A	DECK-SLIM DECK;KSM1000AAA,MCD-HM920,BALL	
	AH59-01138A	REMOCON-RM-HF920;MCD-HF920,CD-YEPP,-,-,9	
	AH59-01152A	MICROPHONE-EAR;-,HP-200CD,EARPHONE,1300,	
	AH92-01749B	**ASSY PCB-MAIN(TA);MCD-HF920,ASS'Y MAIN(T**	
MSW2	3409-001081	SWITCH-DETECTOR;12V DC,0.1A,SPST,30gf,PU	
CN104	3711-004381	CONNECTOR-HEADER;BOX,6P,1R,1.5MM,STRAIGH	
JA401	3722-001919	JACK-DC POWER;5P,4.4/2.8PI,-,BLACK	
	AH61-01226A	BRACKET-BATTERY +;MCD-HM920,SUS304 3/4	
	AH61-01227A	BRACKET-BATTERY -;MCD-HM920,SUS304 3/4	
	AH94-01125B	ASSY CHIP-MAIN,(TA);MCD-HF920,MAIN CHIP(	
D301	0401-000008	DIODE-SWITCHING;DAN217,80V,100mA,SOT-23,	
D402	0401-000008	DIODE-SWITCHING;DAN217,80V,100mA,SOT-23,	
D601	0401-001090	DIODE-SWITCHING;1SS355,80V,225mA,SOD-323	
D401	0403-001306	DIODE-ZENER;MMGDZ3.0B,3.01-3.22V,500mW,L	
D350	0404-000144	DIODE-SCHOTTKY;SB01-05CP,50V,100mA,SOT-2	
D404	0404-000145	DIODE-SCHOTTKY;SB07-03C,30V,700mA,SOT-23	
D403	0404-000145	DIODE-SCHOTTKY;SB07-03C,30V,700mA,SOT-23	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q115	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q114	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q113	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q112	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q301	0501-000462	TR-SMALL SIGNAL;MMBT2907A,PNP,350MW,SOT-	
Q401	0501-000528	TR-SMALL SIGNAL;KSC2982B,NPN,500mW,SOT-8	
Q402	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2	
Q461	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q459	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q457	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q455	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q111	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q121	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q453	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q110	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q405	0505-001424	FET-SILICON;2SK3065,N,30V,2A,0.45ohm,0.5	
Q404	0505-001424	FET-SILICON;2SK3065,N,30V,2A,0.45ohm,0.5	
Q460	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q458	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q456	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q454	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q452	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q403	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q120	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
IC106	0801-002798	IC-CMOS LOGIC;74VHC175MTC, D FLIP-FLOP,T	
IC101	0903-001297	IC-MICROCONTROLLER;LC87F54C8A,8BIT,TQFP,	
IC103	0904-001524	IC-DSP;5L9290,-,QFP,48P,472MIL,16.934	
IC302	1003-001366	IC-MOTOR DRIVER;BH6508FS,SSOP,32P,212MIL	
IC301	1003-001430	IC-MOTOR DRIVER;BD6609FV,SOIC,20P,173MIL	
IC403	1103-001253	IC-EEPROM;M24C02,256X8BITBIT,TSSOP,8P,16	
IC202	1105-001369	IC-DRAM;-,4MX16BIT,TSOP(II),54P,400MIL,7	
IC105	1201-001815	IC-POWER AMP;TDA7469,SOP,24P,208MIL,SING	
IC304	1202-000188	IC-VOLTAGE COMP.;10393,SOP,8P,244MIL,DUA	
IC104	1203-001369	IC-VOL. DETECTOR;61AN1902,SOT-23,3P,63MI	
IC401	1203-002175	IC-DC/DC CONVERTER;6367,SOT-25,5P,63MIL,	
IC402	1203-002274	IC-DC/DC CONVERTER;6368,SOT-25,5P,63MIL,	
IC350	1203-002802	IC-DC/DC CONVERTER;XC6383A331PR,SOT-89,3	
IC102	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC	
IC201	1204-002015	IC-DECODER;TMD2201A,TQFP,80P,-,PLASTIC,3	
R559	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R558	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
BD502	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
BD501	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
BD311	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R164	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R165	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R190	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R501	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R123	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R132	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R149	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R150	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R188	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R166	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R147	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R306	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R322	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R551	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R552	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R141	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R133	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R134	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R135	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R136	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R140	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R138	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R137	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R198	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R199	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R420	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R421	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R459	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R461	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R519	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R194	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R168	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R169	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R170	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R171	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R193	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R192	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R189	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R557	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R555	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R407	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R406	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R313	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R305	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
FR2	2007-000079	R-CHIP;1.8Kohm,5%,1/16W,DA,TP,1608	
FR4	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
R311	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R160	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R159	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R152	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R151	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R312	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
R304	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
R124	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
FR5	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
FR6	2007-000087	R-CHIP;6.8Kohm,5%,1/16W,DA,TP,1608	
R241	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R240	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R212	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R211	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R242	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R243	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R503	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R505	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R210	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R129	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R181	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R182	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R205	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R209	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R208	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R207	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R206	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R121	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
R115	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
R131	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
R125	2007-000093	R-CHIP;20Kohm,5%,1/16W,DA,TP,1608	
R301	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
R119	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
R215	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R216	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R254	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R257	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R214	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R109	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R113	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R118	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R213	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R102	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
R103	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
R120	2007-000100	R-CHIP;68Kohm,5%,1/16W,DA,TP,1608	
R196	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R250	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R401	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R553	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R554	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R612	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R122	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R176	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R177	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R195	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R180	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R178	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R114	2007-000103	R-CHIP;120Kohm,5%,1/16W,DA,TP,1608	
R116	2007-000104	R-CHIP;150Kohm,5%,1/16W,DA,TP,1608	
R112	2007-000104	R-CHIP;150Kohm,5%,1/16W,DA,TP,1608	
R126	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
R148	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	

Location no	Code no.	Description; Specifiation	Remarks
R179	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
R101	2007-000115	R-CHIP;82ohm,5%,1/16W,DA,TP,1608	
FR1	2007-000122	R-CHIP;1.2Kohm,5%,1/16W,DA,TP,1608	
FR3	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
R310	2007-000125	R-CHIP;3.9Kohm,5%,1/16W,DA,TP,1608	
R110	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
R117	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
R220	2007-000234	R-CHIP;1.3Kohm,5%,1/16W,DA,TP,1608	
R108	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
R411	2007-000310	R-CHIP;10OHM,5%,1/2W,DA,TP,5025	
R403	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,1608	
R402	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,1608	
R456	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R457	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R458	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R462	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R130	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R146	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R405	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R455	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R158	2007-000882	R-CHIP;4.7ohm,5%,1/16W,DA,TP,1608	
R157	2007-000882	R-CHIP;4.7ohm,5%,1/16W,DA,TP,1608	
R107	2007-001026	R-CHIP;560Kohm,5%,1/16W,DA,TP,1608	
R106	2007-001026	R-CHIP;560Kohm,5%,1/16W,DA,TP,1608	
R321	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
R320	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
R303	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
R302	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
C125	2203-000125	C-CERAMIC,CHIP;1.2nF,10%,50V,X7R,TP,1608	
C131	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
C565	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C564	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C132	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C130	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C116	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C115	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C107	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C121	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C104	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C303	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C302	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C301	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C109	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C605	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C312	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C169	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C168	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C167	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C139	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
C138	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
C118	2203-000800	C-CERAMIC,CHIP;33nF,10%,25V,X7R,TP,1608	
C108	2203-000800	C-CERAMIC,CHIP;33nF,10%,25V,X7R,TP,1608	
C318	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C314	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C313	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C126	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C306	2203-000972	C-CERAMIC,CHIP;47nF,10%,16V,X7R,TP,1608	
C305	2203-000972	C-CERAMIC,CHIP;47nF,10%,16V,X7R,TP,1608	
C213	2203-001063	C-CERAMIC,CHIP;56nF,10%,16V,X7R,TP,1608,	
C212	2203-001063	C-CERAMIC,CHIP;56nF,10%,16V,X7R,TP,1608,	
C113	2203-001140	C-CERAMIC,CHIP;68nF,10%,16V,X7R,TP,1608,	
C142	2203-001222	C-CERAMIC,CHIP;820pF,10%,50V,X7R,TP,1608	
C110	2203-001640	C-CERAMIC,CHIP;0.39nF,10%,50V,X7R,TP,160	
C119	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,	
C117	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,	
C216	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C217	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C218	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C219	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C220	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C309	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C205	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C208	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C209	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C211	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C214	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C215	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C566	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C602	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C604	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C606	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C625	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C626	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C401	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C403	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C501	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C504	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C513	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C552	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C203	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C122	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C123	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C140	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C143	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	

Location no	Code no.	Description; Specifiation	Remarks
C144	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C148	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C102	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C105	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C106	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C111	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C112	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C120	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C188	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C189	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C190	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C198	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C199	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C202	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C175	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C178	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C180	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C186	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C185	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C182	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C556	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C555	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C316	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C304	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C129	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C405	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C404	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C320	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C407	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C410	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C412	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C158	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C159	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C308	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C315	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C317	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C319	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C402	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.	
C554	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C553	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C321	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C152	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C114	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C149	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C150	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C151	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C210	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C206	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C201	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C197	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C221	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C222	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C325	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C611	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C193	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C103	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C145	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C147	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C172	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C184	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C183	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C179	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C173	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C124	2404-000367	C-TA,CHIP;4.7uF,20%,6.3V,-,-,3216	
C603	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C350	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C141	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C137	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C101	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C409	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C411	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C502	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C550	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C551	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C408	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C133	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C134	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C135	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C181	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C207	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
L510	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L511	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L512	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L303	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L102	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L110	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L302	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L600	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L501	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L350	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L120	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L112	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm	
L402	2703-001020	INDUCTOR-SMD;47uH,20%,7x7x3.2mm	
L401	2703-001020	INDUCTOR-SMD;47uH,20%,7x7x3.2mm	

Location no	Code no.	Description; Specifiation	Remarks
X102	2802-001012	RESONATOR-CERAMIC;16.934MHZ,0.5%,TP,3.7X	
X101	2802-001199	RESONATOR-CERAMIC;6MHZ,0.5%,TP,7.2X3.4X1	
BD404	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD402	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD401	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD509	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD510	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD511	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD512	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD508	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD503	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD504	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD506	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD507	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
FSW5	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW6	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW7	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW4	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW1	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW2	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW3	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW1	3408-001038	SWITCH-SLIDE;4V,300mA,SPST,ON-ON,-	
CN101	3708-001149	CONNECTOR-FPC/FFC/PIC;16P,1MM,SMD-A,SN	
CN301	3711-005161	CONNECTOR-HEADER;BOX,6P,1R,1MM,SMD-A,SN,	
JA501	3722-001918	JACK-PHONE;14P,-,-,BLACK,-	
IC800	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
PACK1	AH40-00015C	TUNER-MODULE PACK;DA-101A,MCD-HM920,FM,-	

****** MCD-HM920 Parts List ******

	4302-001087	BATTERY-NIH(2ND);1.2V,1350MAH,RECTANGULA	
	AH44-00023J	ADAPTOR;-,-,120V,60HZ,4.5VDC+/-0.3V,0.	
CD DECK	AH59-01105A	DECK-SLIM DECK;KSM1000AAA,MCD-HM920,BALL	
	AH59-01138B	REMOCON-RM-HM920;MCD-HM920,CD-YEPP,-,-,9	
	AH59-01152A	MICROPHONE-EAR;-,HP-200CD,EARPHONE,1300,	
	AH92-01749A	**ASSY PCB-MAIN(TA);MCD-HM920,ASS'Y MAIN(T**	
MSW2	3409-001081	SWITCH-DETECTOR;12V DC,0.1A,SPST,30gf,PU	
CN104	3711-004381	CONNECTOR-HEADER;BOX,6P,1R,1.5MM,STRAIGH	
JA401	3722-001919	JACK-DC POWER;5P,4.4/2.8PI,-,BLACK	
	AH94-01125A	ASSY CHIP-MAIN,(TA);MCD-HM920,MAIN CHIP(	
D301	0401-000008	DIODE-SWITCHING;DAN217,80V,100mA,SOT-23,	
D402	0401-000008	DIODE-SWITCHING;DAN217,80V,100mA,SOT-23,	
D601	0401-001090	DIODE-SWITCHING;1SS355,80V,225mA,SOD-323	
D401	0403-001306	DIODE-ZENER;MMGDZ3.0B,3.01-3.22V,500mW,L	
D350	0404-000144	DIODE-SCHOTTKY;SB01-05CP,50V,100mA,SOT-2	
D404	0404-000145	DIODE-SCHOTTKY;SB07-03C,30V,700mA,SOT-23	
D403	0404-000145	DIODE-SCHOTTKY;SB07-03C,30V,700mA,SOT-23	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q113	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q112	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q301	0501-000462	TR-SMALL SIGNAL;MMBT2907A,PNP,350MW,SOT-	
Q401	0501-000528	TR-SMALL SIGNAL;KSC2982B,NPN,500mW,SOT-8	
Q402	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2	
Q461	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q459	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q457	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q455	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q111	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q121	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q453	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q110	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q405	0505-001424	FET-SILICON;2SK3065,N,30V,2A,0.45ohm,0.5	
Q404	0505-001424	FET-SILICON;2SK3065,N,30V,2A,0.45ohm,0.5	
Q460	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q458	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q456	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q454	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q120	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q403	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q452	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
IC106	0801-002798	IC-CMOS LOGIC;74VHC175MTC, D FLIP-FLOP,T	
IC101	0903-001297	IC-MICROCONTROLLER;LC87F54C8A,8BIT,TQFP,	
IC103	0904-001524	IC-DSP;5L9290,-,QFP,48P,472MIL,16.934	
IC302	1003-001366	IC-MOTOR DRIVER;BH6508FS,SSOP,32P,212MIL	
IC301	1003-001430	IC-MOTOR DRIVER;BD6609FV,SOIC,20P,173MIL	
IC403	1103-001253	IC-EEPROM;M24C02,256X8BITBIT,TSSOP,8P,16	
IC202	1105-001369	IC-DRAM;-,4MX16BIT,TSOP(II),54P,400MIL,7	
IC105	1201-001815	IC-POWER AMP;TDA7469,SOP,24P,208MIL,SING	
IC304	1202-000188	IC-VOLTAGE COMP.;10393,SOP,8P,244MIL,DUA	
IC104	1203-001369	IC-VOL. DETECTOR;61AN1902,SOT-23,3P,63MI	
IC401	1203-002175	IC-DC/DC CONVERTER;6367,SOT-25,5P,63MIL,	
IC402	1203-002274	IC-DC/DC CONVERTER;6368,SOT-25,5P,63MIL,	
IC350	1203-002802	IC-DC/DC CONVERTER;XC6383A331PR,SOT-89,3	
IC102	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC	
IC201	1204-002015	IC-DECODER;TMD2201A,TQFP,80P,-,PLASTIC,3	
BD502	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
BD501	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
BD311	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R190	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R165	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R164	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R150	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R123	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R132	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R149	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
R202	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R201	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R188	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R166	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R203	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R204	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R306	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R322	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R147	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R133	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R134	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R135	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R136	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R141	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R140	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R138	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R137	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
R420	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R199	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R198	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R421	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R459	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R461	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R519	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R194	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R168	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R169	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R170	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R171	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R193	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R192	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R189	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
R407	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R406	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R313	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
R305	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
FR2	2007-000079	R-CHIP;1.8Kohm,5%,1/16W,DA,TP,1608	
FR4	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
R311	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R152	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R151	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
R312	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
R304	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
R124	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
FR5	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
FR6	2007-000087	R-CHIP;6.8Kohm,5%,1/16W,DA,TP,1608	
R241	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R240	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R212	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R211	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R242	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R243	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R503	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R505	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R210	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R129	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R181	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R182	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R205	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R209	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R208	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R207	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R206	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
R121	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
R115	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
R131	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
R125	2007-000093	R-CHIP;20Kohm,5%,1/16W,DA,TP,1608	
R301	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
R119	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
R215	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R216	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R254	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R257	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R214	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R109	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R113	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R118	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R213	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
R103	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
R102	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
R120	2007-000100	R-CHIP;68Kohm,5%,1/16W,DA,TP,1608	
R195	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R196	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R250	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	

Location no	Code no.	Description; Specifiation	Remarks
R401	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R612	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R122	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R176	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R177	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R178	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R180	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
R114	2007-000103	R-CHIP;120Kohm,5%,1/16W,DA,TP,1608	
R116	2007-000104	R-CHIP;150Kohm,5%,1/16W,DA,TP,1608	
R112	2007-000104	R-CHIP;150Kohm,5%,1/16W,DA,TP,1608	
R126	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
R148	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
R179	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
R101	2007-000115	R-CHIP;82ohm,5%,1/16W,DA,TP,1608	
FR1	2007-000122	R-CHIP;1.2Kohm,5%,1/16W,DA,TP,1608	
FR3	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
R310	2007-000125	R-CHIP;3.9Kohm,5%,1/16W,DA,TP,1608	
R117	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
R110	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
R220	2007-000234	R-CHIP;1.3Kohm,5%,1/16W,DA,TP,1608	
R108	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
R411	2007-000310	R-CHIP;10OHM,5%,1/2W,DA,TP,5025	
R403	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,1608	
R402	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,1608	
R456	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R457	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R458	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R462	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R130	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R146	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R405	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R455	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,1608	
R197	2007-000882	R-CHIP;4.7ohm,5%,1/16W,DA,TP,1608	
R158	2007-000882	R-CHIP;4.7ohm,5%,1/16W,DA,TP,1608	
R157	2007-000882	R-CHIP;4.7ohm,5%,1/16W,DA,TP,1608	
R107	2007-001026	R-CHIP;560Kohm,5%,1/16W,DA,TP,1608	
R106	2007-001026	R-CHIP;560Kohm,5%,1/16W,DA,TP,1608	
R321	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
R320	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
R303	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
R302	2007-002425	R-CHIP;1OHM,5%,1/16W,DA,TP,1608	
C125	2203-000125	C-CERAMIC,CHIP;1.2nF,10%,50V,X7R,TP,1608	
C131	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
C132	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C130	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C116	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C115	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C107	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
C121	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C104	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C303	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C302	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C301	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C109	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
C605	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C312	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C169	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C168	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C167	2203-000592	C-CERAMIC,CHIP;0.22NF,5%,50V,C0G,TP,1608	
C139	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
C138	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
C118	2203-000800	C-CERAMIC,CHIP;33nF,10%,25V,X7R,TP,1608	
C108	2203-000800	C-CERAMIC,CHIP;33nF,10%,25V,X7R,TP,1608	
C318	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C314	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C313	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C126	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C306	2203-000972	C-CERAMIC,CHIP;47nF,10%,16V,X7R,TP,1608	
C305	2203-000972	C-CERAMIC,CHIP;47nF,10%,16V,X7R,TP,1608	
C212	2203-001063	C-CERAMIC,CHIP;56nF,10%,16V,X7R,TP,1608,	
C213	2203-001063	C-CERAMIC,CHIP;56nF,10%,16V,X7R,TP,1608,	
C113	2203-001140	C-CERAMIC,CHIP;68nF,10%,16V,X7R,TP,1608,	
C142	2203-001222	C-CERAMIC,CHIP;820pF,10%,50V,X7R,TP,1608	
C110	2203-001640	C-CERAMIC,CHIP;0.39nF,10%,50V,X7R,TP,160	
C119	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,	
C117	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,	
C215	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C216	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C217	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C218	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C219	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C220	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C203	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C205	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C208	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C209	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C211	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C214	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C566	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C602	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C604	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C606	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C625	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	

Location no	Code no.	Description; Specifiation	Remarks
C626	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C309	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C401	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C403	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C501	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C504	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C513	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C122	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C123	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C140	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C143	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C144	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C148	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C102	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C105	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C106	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C111	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C112	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C120	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C188	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C189	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C190	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C198	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C199	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C202	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C175	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C178	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C180	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C182	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C185	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C186	2203-005005	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
C316	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C304	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C129	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
C320	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C404	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C405	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C407	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C410	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C412	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C158	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C159	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C308	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C315	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C317	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C319	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C402	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.	
C321	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C152	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C151	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C114	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C149	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C150	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C210	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C206	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C201	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C197	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C221	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C222	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C325	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C611	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C193	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C103	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C145	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C147	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C172	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C184	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C183	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C179	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C173	2404-000361	C-TA,CHIP;22uF,20%,4V,GP,TP,3216,-	
C124	2404-000367	C-TA,CHIP;4.7uF,20%,6.3V,-,-,3216	
C603	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C350	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C141	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C137	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C101	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C408	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C409	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C411	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C502	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C550	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C133	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C134	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C135	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C181	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C207	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
L303	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L302	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L110	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L102	2703-000001	INDUCTOR-SMD;10uH,10%,2.5x3.2x2mm	
L501	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L500	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L350	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	

Location no	Code no.	Description; Specifiation	Remarks
L120	2703-000002	INDUCTOR-SMD;100uH,10%,2.5x3.2x2mm	
L112	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm	
L402	2703-001020	INDUCTOR-SMD;47uH,20%,7x7x3.2mm	
L401	2703-001020	INDUCTOR-SMD;47uH,20%,7x7x3.2mm	
X102	2802-001012	RESONATOR-CERAMIC;16.934MHZ,0.5%,TP,3.7X	
X101	2802-001199	RESONATOR-CERAMIC;6MHZ,0.5%,TP,7.2X3.4X1	
L511	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD404	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD402	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD401	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
BD509	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD510	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD511	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD512	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD508	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD503	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD504	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD506	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
BD507	3301-001643	CORE-FERRITE BEAD;AB,1.5KOHM,1.6X0.8X0.5	
FSW5	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW6	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW7	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW4	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW3	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW2	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
FSW1	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW1	3408-001038	SWITCH-SLIDE;4V,300mA,SPST,ON-ON,-	
CN101	3708-001149	CONNECTOR-FPC/FFC/PIC;16P,1MM,SMD-A,SN	
CN301	3711-005161	CONNECTOR-HEADER;BOX,6P,1R,1MM,SMD-A,SN,	
JA501	3722-001918	JACK-PHONE;14P,-,-,BLACK,-	
IC800	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	

Location no	Code no.	Description; Specifiation	Remarks